

## Description

The OGS range of emergency stop switch are for use in the manual shut down of systems in the event of fire or other emergency.

## Features

- Twist reset version
- Versions
- 6A @ 230Vac rated



## Technical Specification

Reset Type: Twist reset  
Switch Rating: 10(6)A @ 240Vac SPDT  
Housing Dimensions: 80 x 73 x 50mm

## Order Code

OGS-EM1 Emergency stop button - twist reset

## Installation

### Warning:

Hazardous voltage can cause electrical shock. Disconnect power before proceeding with any work on this equipment.

1. Separate switch base and top
2. Mount using the base as a template for holes
3. Knock out hole at top or bottom of base to allow cable entry
4. Feed cable through a cable gland and hole
5. Make necessary electrical connections
6. Replace switch top

## Typical Wiring Connections



### Plastic Housing Versions:

Contact Block situated inside base of housing

[www.oceaniagassafety.com](http://www.oceaniagassafety.com)

**Oceania Gas Safety**

Tuakau Waikato

New Zealand

+64212386990